

## RF working modes

### **Momentary:**

Press and hold remote button ,the relay will turn on;  
Release button, the relay will turn off

### **Toggle:**

Press remote button ,the relay will turn on;  
Press same remote button again, the relay will turn off

### **Latched:**

Press 1st remote button ,the relay will turn on;  
Press 2nd remote button, the relay will turn off

## How to pair with remotes in different modes

### **Momentary:**

1. Press the learning button(on the Receiver) **1** times. Wait for 3 seconds;
2. Press remote button 1 time, succeed

### **Toggle:**

1. Press the learning button(on the Receiver) **2** times. Wait for 3 seconds;
2. Press remote button 1 time, succeed

### **Latched:**

1. Press the learning button(on the Receiver) **3** times. Wait for 3 seconds;
2. Press 1st button 1 time, press 2nd button 1 time, succeed

## How to clean data

Press the learning button (on the Receiver) **8** times. Wait for 3 seconds, the data will be cleaned. All remote cannot control the switch anymore

## Why should i clean data

- 1.Sometimes you want to change modes, you need to clean data first. Or you can pair with a new remote in a new mode
- 2.After you get our product, please clean data first. Then start to pair with remote.

# Set up



# Clean